

# MODEL NO. : LM-1538B1K High Brightness Quad Monitor



## □ SPECIFICATION □

|                         |  |
|-------------------------|--|
| ◆ DISPLAY SCREEN        | 15 " TFT (Diagonal)                            |
|                         | Active Display Area 304.128(W) x 228.096 mm(H) |
|                         | Element Color TFT LCD                          |
|                         | Resolution 1024 x 768 maximum                  |
|                         | LCD Display Color 16.2M colors                 |
|                         | Pixel Pitch 0.297 x 0.297 mm                   |
| ◆ POWER SOURCE          | AC/DC Adapter 12 V                             |
| ◆ OPERATING TEMPERATURE | 0°C ~ 55°C                                     |
| ◆ STORAGE TEMPERATURE   | -5°C ~ 60°C                                    |
| ◆ BRIGHTNESS            | 1000 cd/m <sup>2</sup>                         |
| ◆ RESPONSE TIME         | 12 ms (Tr+Tf)                                  |
| ◆ CONTRAST              | 800 : 1  |
| ◆ VIEWING ANGLE         | Vertical ± 45° , Horizontal : ± 60°            |
| ◆ VIDEO INPUT           | BNC x 4  |
| ◆ VIDEO OUT             | BNC X 1  |
| ◆ PC INPUT              | 15 PIN D-SUB                                   |
| ◆ PLUG & PLAY           | VESA DDC2B                                     |
| ◆ GREEN FUNCTION        | VESA DPMS                                      |
| ◆ OSD CONTROL FUNCTION  | Brightness, Contrast, Color, Volume, Mute      |
| ◆ OVERALL DIMENSION     | 333 x 272 x 43 (mm)                            |
| ◆ REGULATIONS           | Safety: CE, FCC meet                           |
| ◆ WEIGHT                | 5.0 Kgs  |

## ☐ **FEATURE** ☐

1. Heavy Duty 15" 4:3 LCD Monitor
2. BNC x 4 Inputs for QUAD
3. High Brightness 1000 Nit
4. PC INPUT
5. Touch Screen ( Optional )
6. Knob Control Brightness
7. Multi Language

## ☐ **ON SCREEN DISPLAY SETTINGS (OSD)** ☐

- ◆ To turn on the OSD menu: Press power button.  
Press Menu button.
- ◆ When OSD menu is on .
  - Select option within icon menu: Use up or down buttons.  
Then press Menu to make select.
  - Increase/decrease setting : Use up or down buttons.
- ◆ To load the presetting (default setup) :  
Use menu button and power button. (menu +power button )
- ◆ **Auto** button is default to input source select