

Product introduction – Receiver pager(optional)

FST- GP2015W



Product parameter

- ◆ 1.Hand and PC programmable. USB id programmer.
- ◆ 2.PLL or crystal, 137-930Mhz, POCSAG or Flex
- ◆ 3.Alert mode: Sound, vibrate, LED, Silent.
- ◆ .4 or 8 line English display, 3 zoom mode (English).
- ◆ .Language support: Chinese, English, Germany, Korean, Turkey, Farsi, French, etc.
- ◆ .Out of range, low battery, repeat message, unread message indicator.
- ◆ .Menu select able, User choice special functions for themselves.
- ◆ .Second watch function

Function description

- Can receiver the calls for the call buttons, transmitters
- Can show the call number and room number of the call button
- Can store 40message or calls
- Can receiver the message from transmitter
- Very long battery life, 1time charge can use about 20days , and battery life over 5 years
- Supper signal distance
- same function as FST-GP2009W, and water proof