

<b>MODEL</b>	<b>HE2M (UNIVERSAL) (FME-female)</b>
<b>ANTENNA TYPE</b>	<i>Flexible helical whip antenna with integrated FME connector</i>
<b>FREQUENCY</b>	<i>144-225 MHz (Cutting table included)</i>
<b>IMPEDANCE</b>	<i>Nom. 50 Ω</i>
<b>POLARISATION</b>	<i>Vertical</i>
<b>GAIN</b>	<i>0 dB (2.15 dBi)</i>
<b>BANDWIDTH</b>	<i>16 MHz</i>
<b>VSWR</b>	<i>&lt; 2.0 at frequency resonance</i>
<b>MAX. POWER</b>	<i>50 Watt</i>
<b>COLOUR</b>	<i>Black</i>
<b>LENGTH</b>	<i>Approx. 175 mm</i>
<b>WEIGHT</b>	<i>Approx. 0.035 kg</i>
<b>MOUNTING</b>	<i>On transceivers etc.</i>
<b>MATERIAL</b>	<i>POM, PE, steel and brass</i>
<b>ORD.NO.</b>	<p><b>14 087 (Antenna whip only)</b>  <b>14 087 IP (Bulk-pack)</b></p> <p><b>14 154 (Antenna + BNC(m))</b>  <b>14 154 IP (Bulk-pack)</b></p> <p><b>14 155 (Antenna + TNC(m))</b>  <b>14 155 IP (Bulk-pack)</b></p>

