**Product warranty service card** 

1 Toutet wall ality service card	
Name	Tel
Address	
Product Name	Model
Purchasing Date	
Invoice or Receipt Number	
Dealer	Tel
Contactor	
Breakdown Description	

# 360°panning

# underwater camera fish finder



**Instruction Manual** 

Vnr 152-955

# **Safety Notes:**

- 1. Please read the manual carefully before using it.
- 2, andle it carefully during operation, avoid throwing down or pressing it heavily.
- 3. If the users disassemble or deliberately damage the machine, it will beyond the warranty.
- 4. After being used, turn off the display and pull out all the connection joints.
- 5. Please keep distance from the system when charging
- 6. To make the product better, we set the camera lens and the related specifications basing the underwater environment. it is normal If there is any different when u using not in the water.
- 7. Due to the version upgrades, if mentioned in this manual content does not accord with your machine, please refer to our machine.

# **Description**

- 1, 360° panning camera, wide viewing angle.
- 2. Housing: strong, durable and easily radiating.
- 3, HD SNOY camera.
- 4, with 36 bright night vision lights (24pcs white light, 12pcs infrared lights), perfect vision effect.
- 5, white light and infrared light can be switched, the light can be turned on or off.
- 6 High quality special cable, waterproof and anti-corrosion/cold/tensile.
- 7. With sun-visor for bright environment outside
- 8. The product is an underwater video camera and fish finder fish finder underwater breeding monitoring fishing monitoring underwater viewing underwater adventure water well monitoring .....

2> power box

1 power light 2 key 3 power switch 4 charging connecting base 5 camera connector 6 power of monitor 7 monitor video



3>System

1 power box 2 charger 3 aluminum box 4 display 5 camera 6 sunshade cover 7 cable



## **Product components and accessories**

1>Camera

1 reel 2 transparent case 3 lens 4 highlight night-vision 5 metal casing 6 cable 7 camera connection



#### Feature of the camera:

- (1) The casing of camera is all made of metal, firm and durable.
- (2) The visual angle of camera is 360 degree, the camera rotates automatically, manually, AB section.
- (3) with 36 bright night vision lights (24pcs white light, 12pcs infrared lights), perfect vision effect.
- (4) white light and infrared light can be switched, the light can be turned on or off.
- (5) Applied ultra high definition camera board, with good camera shooting effect.
- (6) With special cold-resistant, water-proof, and anti-pressing cable.

# **Specifications**

Parameter
HD wide viewing angle
Multi-language
High resolution
IP68
5MM
36pcs bright night light
24pcs
12pcs
hardware shell
20M(selectable line length)
Color
Color
AC100-240V
Lithium battery
12VDC
-20—60 degrees
-30—80 degrees
390*320*150mm
410*360*160mm
5.2KG
5.7KG

# **Button operation manual**



- (1) Startup& shutdown
- ①Connect all connectors (camera aviation line and monitor line); turn the power switch to ON, the power light is on.
- ②Press "ON" on the keyboard, the machine starts operating under auto mode.
- ③Press "L" and "R" at the same time, the machine stops.
- 4 Turn the power switch to "OFF", and disconnect the connectors.
- (2)Switch Night Vision Light.

Press "LED" on the keyboard to control the switch of night-vision of the camera.Default: The white and infrared lights are turn off.

- ①Press the LED button for the first time: the white light is on and the infrared light is off.
- ②Press the LED button for the second time, the infrared light is on, and the white light is off.
- ③Press the LED button for the third time, the white light and the infrared light are on simultaneously.
- ④ Press the LED button for the fourth time to enter the power-on state, and the white light and the infrared light are simultaneously turned off.

Circulate in this way

- (3) Rotate manually and automatically
- ①Press "AUTO/MANU" to switch manual and auto rotation. It will be auto when starting up, the camera will rotates right under auto status.
- ②Turn left. Press L under manual status, the camera turns left, press L again the camera stop.
- ③Turn right. Press R under manual status, the camera turns right, press R again the camera stop
- (4) Rotate to specified angle. Press R under auto status to choose angle A, then press R to choose angle B, the camera rotates between A and B. Press R again to cancel the rotation and turn to auto status.

#### Connection

1. video 2. Power 3. Camera cable

### Charging

When the battery power is low, it needs charging, and the method is as below:

- 1. Take out the battery and charger from the box.
- 2. Connect the charger to the battery.
- 3. Connect the charger to the alternating current of 110-220V. The red indicator means charging.
- 4. The green indicator means finishing charging.

Notes: 1.to make sure the battery using age longer, please recharge it timely; otherwise, it will make it can not recharged.

2. please keep distance from the system when charging

